MTL4644/S REPEATER POWER SUPPLY

2-channel, 4/20mA, HART®, 2- or 3- wire transmitters

The MTL4644 provides fully-floating dc supplies for energising two conventional 2-wire or 3-wire 4/20mA or HART transmitters, and repeats the current in other circuits to drive two loads. For smart transmitters, the unit allows bi-directional transmission of digital communication signals superimposed on the 4/20mA loop current. Alternatively, the MTL4644S acts as a current sink rather than driving a current into the load.

SPECIFICATION

See also common specification

Number of channels

Two

Output

Signal range: 4 to 20mA Under/over-range: 0 to 24mA

Load resistance (MTL4644)

@ 24mA: 0 to 375Ω@ 20mA: 0 to 465Ω

Load (MTL4644S)

Current sink: 600Ω max. Maximum voltage source: 24V dc

Circuit output resistance: $> 1M\Omega$

Circuit ripple

< 50µA peak-to-peak

Input

Signal range: 0 to 24mA (including over-range)

Transmitter voltage: 20V at 20mA

Transfer accuracy at 20°C

Better than $20\mu A$ 4-20mA (Terminals 1 & 2 / 4 & 5) Better than $30\mu A$ 4-20mA (Terminals 1 & 3 / 4 & 6)


Temperature drift

< 0.8µA/°C

Response time

Settles to within 10% of final value within 50µs

MTL4644 / MTL4644S



Communications supported

HART (terminals 1 & 2 and 4 & 5 only)

LED indicator

Green: power indication

Maximum current consumption (with 20mA signals)

100mA at 24V dc

Power dissipation within unit (with 20mA signals)

MTL4644 1.5W @ 24V dc MTL4644S 2.0W @ 24V dc



Eaton Electric Limited,

Great Marlings, Butterfield, Luton Beds, LU2 8DL, UK. Tel: + 44 (0)1582 723633 Fax: + 44 (0)1582 422283 E-mail: mtlenquiry@eaton.com www.mtl-inst.com © 2016 Eaton All Rights Reserved Publication No. EPS4644/S Rev 4 010916 EUROPE (EMEA):

The given data is only intended as a product description and should not be regarded as a legal

+44 (0)1582 723633 mtlenquiry@eaton.com

THE AMERICAS:

+1 800 835 7075 mtl-us-info@eaton.com
ASIA-PACIFIC:
+65 6 645 9888 sales.mtlsing@eaton.com